MTL4611

SWITCH/ PROXIMITY DETECTOR INTERFACE

1-channel, with line fault detection

The MTL4611 enables a load to be controlled by a switch or proximity detector. When selected, open or short circuit conditions in the field wiring are detected by the line-fault-detect (LFD) facility and also indicated on the top of the module. Phase reversal for the channel is selected by a switch on the side of the module and output is provided by changeover relay contacts.

SPECIFICATION

See also common specification

Number of channels

One

Inputs

Inputs conforming to BS EN60947-5-6:2001 standards for proximity detectors (NAMUR)

Voltage applied to sensor

7 to 9V dc from $1k\Omega \pm 10\%$

Input/output characteristics

Normal phase

Outputs closed if input > 2.1 mA ($< 2 \text{k}\Omega$ in input circuit) Outputs open if input < 1.2 mA (> $10 \text{k}\Omega$ in input circuit) Hysteresis: 200μA (650Ω) nominal

Line fault detection (LFD) (when selected)

User-selectable via switches on the side of the unit. A line fault is indicated by an LED. The channel output relay is de-energised if an input line fault is detected.

Open-circuit alarm on if I_{in} < 50µA Open-circuit alarm off if I_{in} > 250µA Short-circuit alarm on if $R_{in} < 100\Omega$

Short-circuit alarm off if $R_{in}^{I} > 360\Omega$ Note: Resistors must be fitted when using the LFD facility with a contact input 500Ω to 1kΩ in series with switch $20k\Omega$ to $25k\Omega$ in parallel with switch


Output

Single pole relay with changeover contacts Note: reactive loads must be adequately suppressed

Relay characteristics

Response time: 10ms maximum Contact rating: 10W, 0.5A, 35V dc

MTL4611



LED indicators

Green: power indication

Yellow: channel status, on when output energised Red: LFD indication, on when line fault detected

Maximum current consumption

25mA at 24V

Power dissipation within unit

0.6W at 24V

The given data is only intended as a product description and should not be regarded as a legal warranty of proper ties or quarantee. In the interest of further technical developments, we reserve the right to make design changes

